

Levetop LT268A/B/C/D、LT269 比较表

| 支持功能 | | LT268A | LT268B LT269 | LT268C | LT268D |
|--------|---------------|----------|-----------------|-----------|------------|
| 类别 | 功能说明 | | | | |
| LCD 规格 | 分辨率(最高) | 320*240 | 480*320 | 800 x 480 | 800 x 480 |
| MCU 接口 | 16bit 并口 | -- | -- | v | v |
| | 8bit 并口 | v | v v(快速) | v(快速) | v(快速) |
| | 4 线 SPI 串口 | -- | v | v | v |
| MCU 内核 | 内核 | RISC | M4 | M4 | M4 |
| | 速度 | 72MHz | 150MHz | 150MHz | 150MHz |
| | Flash | 64KB | 512KB | 512KB | 512KB |
| | SRAM | 8KB | 256KB | 256KB | 256KB |
| 其他接口 | Uart | v(2 组) | v(2 组) | v(3 组) | v(3 组) |
| | SPI | v(1 组) | v(1 组) | v(1 组) | v(1 组) |
| | QSPI | -- | -- | v(1 组) | v(1 组) |
| | USB 2.0 | v | v | v | v |
| | SD Card | -- | v | v | v |
| | PWM 输出 | v(2 个) | v(2 个) | v(4 个) | v(4 个) |
| | DAC 输出 | v(1 个) | v(1 个) | v(1 个) | v(1 个) |
| | ADC 输入 | v(3 个) | v(2 个) | v(3~9 个) | v(3~11 个) |
| | RTP 接口 | v | v | v | v |
| | CTP I2C 接口 | v | v | v | v |
| | GPIO 输出 | v(1~5 个) | v(1~8 个) | v(3~12 个) | v(11~30 个) |
| | RTC | -- | v | v | v |
| 串口应用 | 串口指令 | 67 个 | 67 个 | 68 个 | 68 个 |
| | UI_Editor | V(I) | V(I, II) | V(I, II) | V(I, II) |
| | UI_Emulator | v | v | v | v |
| | USB 口升级(VCOM) | v | v | v | v |
| | Uart 串口升级 | v | v | v | v |
| | USB 碟升级 | -- | -- | v | v |
| | 二次开发 | v | v | v | v |
| 电源 | 电源 | 3.3V | 3.3V | 3.3V | 3.3V |
| 封装 | 封装 | QFN-48 | QFN-48 | QFN-68 | LQFP-100 |

